arXiv:math/0105075v1 [math.NA] 9 May 2001

COMPUTATIONAL EXPERIMENTS WITH ABS ALGORITHMS FOR OVERDETERMINED LINEAR SYSTEMS [1]

E. Bodon [2], A. Del Popolo [3], L. Lukšan [4] and E. Spedicato [5]

1 Introduction

In this report, we present numerical experiments with two particular ABS algorithms:

(1) The Huang or modified Huang algorithm,

(2) The implicit QR algorithm,

These methods are used for solving the following problem:

(a) Finding the least-squares solution of an overdetermined linear system $Ax = b$, where $A \in R^{m,n}$, $b \in R^m$, $x \in R^n$ and $m \geq n$.

The considered algorithms belong to the scaled ABS class of algorithms for solving linear systems, that is defined by the following scheme:

(A) Let $x_1 \in R^n$ be arbitrary and $H_1 \in R^{n,n}$ be nonsingular arbitrary. Set $i = 1$.

(B) Compute the residual $r_i = Ax_i - b$. If $r_i = 0$, then stop, x_i solves the problem. Otherwise compute $s_i = H_i A^T v_i$, where $v_i \in R^n$ is arbitrary, save that $v_1, \ldots, v_i$ are linearly independent. If $s_i \neq 0$, then go to (C). If $s_i = 0$ and $r_i^T v_i = 0$, then set $x_{i+1} = x_i$, $H_{i+1} = H_i$ and go to (F). If $s_i = 0$ and $r_i^T v_i \neq 0$, then stop, the system is incompatible.

(C) Compute the search vector p_i by

$$p_i = H_i^T z_i,$$

where $z_i \in R^n$ is arbitrary, save that $z_i^T H_i A^T v_i \neq 0$.

(D) Update the estimate of the solution by

$$x_{i+1} = x_i - \alpha_i p_i,$$

where the stepsize α_i is given by

$$\alpha_i = r_i^T v_i / p_i^T A^T v_i.$$

(E) Update the Abaffian matrix by

$$H_{i+1} = H_i - H_i A^T v_i w_i^T H_i / w_i^T H_i A^T v_i,$$

where $w_i \in R^n$ is arbitrary, save that $w_i^T H_i A^T v_i \neq 0$.

[1] Work supported by grant GA CR 201/00/0080 and by MURST 1997 and 1999 Cofinanziamento

[2] Department of Mathematics, University of Bergamo, Bergamo 24129, Italy (bodon@unibg.it)

[3] Department of Mathematics, University of Bergamo, Bergamo 24129, Italy (delpopolo@unibg.it)

[4] Institute of Computer Science, Academy of Sciences of the Czech Republic, Pod vodárenskou věží 2, 182 07 Prague 8, Czech Republic (luksan@uivt.cas.cz)

[5] Department of Mathematics, University of Bergamo, Bergamo 24129, Italy (emilio@unibg.it)

(F) If $i = m$, then stop, x_{i+1} solves the problem. Otherwise increment the index i by one and go to (B).

From (E), it follows by induction that $H_{i+1}A^TV_i = 0$ and $H_{i+1}^TW_i = 0$, where $V_i = [v_1, \ldots, v_i]$ and $W_i = [w_1, \ldots, w_i]$. One can show that the implicit factorization $V_i^TAP_i = L_i$ holds, where $P_i = [p_1, \ldots, p_i]$ and L_i is nonsingular lower triangular. Moreover the general solution of the scaled subsystem $V_i^TAx = V_i^Tb$ can be expressed in the form

$$x = x_i + H_i^Tq, \tag{1}$$

where $q \in R^n$ is arbitrary (see [2] for the proof).

The basic ABS class is the subclass of the scaled ABS class obtained by taking $v_i = e_i$, e_i being the i-th unitary vector (i-th column of the unit matrix). In this case, residual $r_i = Ax_i - b$ need not be computed in (B), i-th element $r_i^Te_i = a_i^Tx_i - b_i$ suffices.

This report is organized as follows. In Section 2, a short description of individual algorithms is given. Section 3 contains some details concerning test matrices and numerical experiments and diuscusses the numerical results. The Appendix contains listing of all numerical results. For other numerical results on ABS methods see [1,11]. For a listing of the used ABS codes see [12].

2 The tested ABS algorithms for overdetermined linear systems

In this report, we deal with two basic algorithms, one belonging to the basic ABS class and one belonging to the scaled ABS class. To simplify description, we will assume that $A \in R^{m,n}$, $m \leq n$, has full row rank so that $s_i \neq 0$ in (B).

The Huang algorithm is obtained by the parameter choices $H_1 = I$, $v_i = e_i$, $z_i = a_i$, $w_i = a_i$. Therefore

$$p_i = H_ia_i \tag{2}$$

and

$$H_{i+1} = H_i - p_ip_i^T/a_i^Tp_i, \tag{3}$$

From (2) and (3), it follows by induction that $p_i \in Range(A_i)$ and

$$H_{i+1} = I - P_iD_i^{-1}P_i^T. \tag{4}$$

where $A_i = [a_1, \ldots, a_i]$, $P_i = [p_1, \ldots, p_i]$ and $D_i = diag(a_1^Tp_1, \ldots, a_i^Tp_i)$. Moreover H_i is symmetric, positive semidefinite and idempotent (it is the orthogonal projection matrix into $Null(A_{i-1})$). Since the requirement $p_i \in Null(A_{i-1})$ is crucial, we can improve orthogonality by iterative refinement $p_i = H_i^ja_i$, $j > 1$ (usually $j = 2$), obtaining the modified Huang algorithm.

The Huang algorithm can be used for finding the minimum-norm solution to the compatible underdetermined system $Ax = b$, i.e. for minimizing $\|x\|$ s.t. $Ax = b$. To see this, we use the Lagrangian function and convexity of $\|x\|$. Then x is a required solution if and only if $x = A^Tu$ for some $u \in R^m$ or $x \in Range(A^T)$. But

$$x_{m+1} = x_1 - \sum_{i=1}^{m} \alpha_ip_i$$

by (D) and $p_i \in Range(A_i) \subset Range(A^T)$, so that if $x_1 = 0$, then $x_{m+1} \in Range(A^T)$.

A short description of two versions of the Huang and modified Huang algorithms follows.

Algorithm 1
(Huang and modified Huang, formula (3)).
Set $x_1 = 0$ and $H_1 = I$.
For $i = 1$ **to** m **do**
Set $p_i = H_i a_i$ (Huang) or
$p_i = H_i(H_i a_i)$ (modified Huang),
$d_i = a_i^T p_i$ and $x_{i+1} = x_i - ((a_i^T x_i - b_i)/d_i)p_i$.
If $i < m$, then set $H_{i+1} = H_i - p_i p_i^T/d_i$.
end do

Algorithm 2
(Huang and modified Huang, formula (4)).
Set $x_1 = 0$ and P_0 empty.
For $i = 1$ **to** m **do**
Set $p_i = (I - P_{i-1}D_{i-1}^{-1}P_{i-1}^T)a_i$ (Huang) or
$p_i = (I - P_{i-1}D_{i-1}^{-1}P_{i-1}^T)(I - P_{i-1}D_{i-1}^{-1}P_{i-1}^T)a_i$ (modified Huang),
$d_i = a_i^T p_i$ and $x_{i+1} = x_i - ((a_i^T x_i - b_i)/d_i)p_i$.
If $i < m$, then set $P_i = [P_{i-1}, p_i]$.
end do

The implicit QR algorithm is obtained by the parameter choices $H_1 = I$, $v_i = Ap_i$, $z_i = e_i$, $w_i = e_i$. Since $z_i = e_i$ and $w_i = e_i$, the matrices H_i and P_i have the same structure as that in the implicit LU algorithm. Using the implicit factorization property $V_i^T A P_i = L_i$, we can see that $V_{i-1}^T v_i = V_{i-1}^T A p_i = 0$ so that the vectors v_j, $j = 1, \ldots, i$, are mutually orthogonal.

The implicit QR algorithm can be used for finding the least-squares solution of an overdetermined linear system $Ax = b$, where $A \in R^{m,n}$, $b \in R^m$, $x \in R^n$ and $m \geq n$, which is obtained after at most n steps. To see this, we recall that algorithms from the scaled ABS class solve the scaled system $V_n^T Ax = V_n^T b$. Since $V_n = AP_n$, where P_n is square nonsingular, the condition $P_n^T A^T Ax = P_n^T A^T b$ implies $A^T Ax = A^T b$, which defines the least-squares solution of the overdetermined system $Ax = b$.

A short description of the implicit QR algorithm follows.

Algorithm 3
(Implicit QR).
Set $x_1 = 0$, $r_1 = -b$ and $H_1 = I$.
For $i = 1$ **to** m **do**
Set $p_i = H_i^T e_i$, $v_i = Ap_i$
(only $(i-1)(n-i+1)$ nonzero elements of H_i is used),
$\alpha_i = r_i^T v_i / v_i^T v_i$, $x_{i+1} = x_i - \alpha_i p_i$ and $r_{i+1} = r_i - \alpha_i v_i$.
(only i nonzero elements of x_i are updated).
If $i < m$, then set $s_i = H_i^T A^T v_i$ and $H_{i+1} = H_i - s_i p_i^T / v_i^T v_i$
(only $i(n-i)$ nonzero elements of H_{i+1} are updated).
end do

We now consider the problem of solving overdetermined linear systems, in the least squares sense. Consider the linear system $Ax = b$, where $A \in R^{m,n}$, $b \in R^m$, $x \in R^n$ and $m \geq n$. This system can be solved in the least squares sense in n steps by the inplicit QR algorithm as was

shown above. Another possibility is based on the application of the Huang algorithm. Since the least-squares solution has to satisfy the normal equation

$$A^T Ax = A^T b,$$

it can be obtained from the solution of the following augmented system .

$$Ax = y, \tag{5}$$

$$A^T y = A^T b. \tag{6}$$

Since $y \in Range(A)$ by (5), it is a minimum-norm solution of (6) and it can be obtained by the Huang algorithm. Having y, the compatible system (5) can be solved by any ABS algorithm. Moreover, using the implicit factorization property $A^T P_n = L_n$, we can write

$$L_n^T x = P_n^T Ax = P_n^T y = \tilde{b}$$

which as a system with a lower triangular matrix can be easily solved by the back substitution. The lower triangular matrix L_n can be obtained as a by-product of the Huang algorithm. If we use formula (4), then d_i is i-th diagonal element of L_n and $P_{i-1}^T \tilde{a}_i$ contains the other i-th-column elements of L_n ($\tilde{a}_i$ is i-th column of the matrix A).

Matrix L_n has not to be stored since it can be reconstructed from columns of the matrix P_n. However, the back substitution has to be realized in a slightly different way in this case.

A short description of two versions of the Huang algorithm for least-squares solution of overdetermined systems follows.

Algorithm 4
(Huang and modified Huang for least-squares with stored L_n).
Set $x_1 = 0$ and P_0 empty.
For $i = 1$ **to** n **do**
If $i > 1$, then compute $g_i = P_{i-1}^T \tilde{a}_i$ and copy it into the lower triangular matrix L_n.
Set $p_i = \tilde{a}_i - P_{i-1} D_{i-1}^{-1} g_i$ (Huang) or
$p_i = (I - P_{i-1} D_{i-1}^{-1} P_{i-1}^T)(\tilde{a}_i - P_{i-1} D_{i-1}^{-1} g_i)$ (modified Huang).
Set $d_i = \tilde{a}_i^T p_i$ and copy it into the lower triangular matrix L_n. Set $\tilde{b}_i = b^T p_i$.
If $i < n$, then set $P_i = [P_{i-1}, p_i]$.
end do
Solve the triangular system $L_n^T x = \tilde{b}$.

Algorithm 5
(Huang and modified Huang for least-squares without stored L_n).
Set $x_1 = 0$ and P_0 empty.
For $i = 1$ **to** n **do**
Set $p_i = (I - P_{i-1} D_{i-1}^{-1} P_{i-1}^T)\tilde{a}_i$ (Huang) or
$p_i = (I - P_{i-1} D_{i-1}^{-1} P_{i-1}^T)(I - P_{i-1} D_{i-1}^{-1} P_{i-1}^T)\tilde{a}_i$ (modified Huang).
Set $d_i = \tilde{a}_i^T p_i$.
If $i < n$, then set $P_i = [P_{i-1}, p_i]$.
end do
Set $f_n = b$.
For $i = n$ **to** 1 **do**
Set $x_i = p_i^T f_i / d_i$.
If $i > 1$, then set $f_{i-1} = f_i - x_i \tilde{a}_i$
end do

3 The computational experiments

Performance of ABS algorithms has been tested by using several types of ill-conditioned matrices. These matrices can be classified in the following way. The first letter distinguishes matrices with integer 'I' and real 'R' elements, both actually stored as reals in double precision arithmetic. The second letter denotes randomly generated matrices 'R' or matrices determined by an explicit formula 'D'. For randomly generated matrices, a number specifying the interval for the random number generator follows, while the name of matrices determined by the explicit formula contains the formula number (F1, F2, F3). The last letter of the name denotes a way for obtaining ill-conditioned matrices: 'R' - matrices with nearly dependent rows, 'C' - matrices with nearly dependent columns, 'S' - nearly singular symmetric matrices, 'B' - both matrices in KKT system ill-conditioned. More specifically:

IR500 Randomly generated matrices with integer elements uniformly distributed in the interval [-500,500].

IR500R Randomly generated matrices with integer elements uniformly distributed in the interval [-500,500] perturbed in addition to have two rows nearly dependent.

IR500C Randomly generated matrices with integer elements uniformly distributed in the interval [-500,500] perturbed in addition to have two columns nearly dependent.

RR100 Randomly generated matrices with real elements uniformly distributed in the interval. [-100,100]

IDF1 Matrices with elements $a_{ij} = |i - j|$, $1 \leq i \leq m$, $1 \leq j \leq n$ (Micchelli-Fiedler matrix).

IDF2 Matrices with elements $a_{ij} = |i - j|^2$, $1 \leq i \leq m$, $1 \leq j \leq n$.

IDF3 Matrices with elements $a_{ij} = |i + j - (m + n)/2|$, $1, \leq i \leq m$, $1 \leq j \leq n$.

IR50 Randomly generated matrices with integer elements uniformly distributed in the interval [-50,50].

Matrices with linearly dependent rows were obtained in the following way. The input data contain four integers which specify two row indices i_1, i_2, one column index i_3 and one exponent i_4. Then the row a_{i_1} is copied into a_{i_2}. Furthermore $a_{i_1 i_3}$ is set to zero and $a_{i_2 i_3}$ to 2^{-i_4}. Similar procedures are used for columns and symmetric matrices.

Solution vectors were generated randomly with integer or real elements uniformly distributed in the interval [-10,10]. Right hand sides for overdetermined systems were obtained by the following way. First, vector $\tilde{b}$ was generated randomly with integer or real elements uniformly distributed in the interval [-10,10]. Then its first element together with elements in the first row of the matrix A were redefined by the formulas $\tilde{b}_1 = -1$ and $a_{1j} = \sum_{i=2}^{n} a_{ij}\tilde{b}_j$ so that $A^T\tilde{b} = 0$. The right-hand side vector was determined by the formula $b = \tilde{b} + Ax^\star$. Since $A^T A x^\star = A^T(b - \tilde{b}) = A^T b$, the normal equation is satisfied and $x^\star$ is a least squares solution of the system $Ax = b$. Vector $\tilde{b}$ was generated nonzero, so that the system $Ax = b$ is incompatible.

We have tested the following particular algorithms:

impl.qr5 The implicit QR algorithm: Algorithm 5 (subroutine alg5d.f).

huang6 The Huang algorithm for overdetermined systems: Algorithm 6 (subroutine. alg6d.f).

mod.huang6 The modified Huang algorithm for overdetermined systems: Algorithm 6 (subroutine alg6d.f).

huang7 The Huang algorithm for overdetermined systems: Algorithm 7 (subroutine alg7d.f).

mod.huang7 The modified Huang algorithm for overdetermined systems: Algorithm 7 (subroutine alg7d.f).

qr lapack Subroutine DGELS from the LAPACK package.

svd lapack Subroutine DGELSS from the LAPACK package.
gqr lapack Subroutine DGELSX from the LAPACK package.

Notice that ABS algorithms were implemented in their basic form without partitioning into block or other special adjustements serving for speed increase as done in the LAPACK software.

Detailed results of computational experiments are presented in the Appendix. For each selected problem, the type of matrix and the dimension is given. Furthermore, both the solution and the residual errors together with the detected rank and the computational time are given for each tested algorithm. Computational experiments were performed on a Digital Unix Workstation in the double precision arithmetic (machine epsilon equal to about 10^{-16}).

We have tested overdetermined systems with $n >> m/2$, $n = m/2$ and $n << m/2$. These systems were solved by using Algorithms 5 - Algorithm 7 together with explicit QR and SVD decomposition based methods taken from the LAPACK package.

The following tables give synthetic results for the 21 tested problems, the number at the intersection of the i-th row with the k-th column indicating how many times the algorithm at the heading of the i-th row gave a lower error than the algorithm at the heading of the k-th row (in case there is a second number, this counts the number of cases when difference was less that one percent).

solution error - 21 overdetermined linear systems

methods	huang 6	mod. huang 6	huang 7	mod. huang 7	impl. qr5	qr lapack	svd lapack	gqr lapack	total
huang6		4	0/21	4	5	9	2	2	26/21
mod.huang6	17		17	1/12	13/6	16	11	8	83/18
huang7	0/21	4		4	5	9	2	2	26/21
mod.huang7	17	8/12	17		14/6	18	11	10	95/18
impl.qr5	16	2/6	16	1/6		10	8	6	59/12
qr lapack	12	5	12	3	11		6/4	9	58/4
svd lapack	19	10	19	10	13	11/4		4/12	86/16
gqr lapack	19	13	19	11	15	12	5/12		94/12

residual error - 21 overdetermined linear systems

methods	huang 6	mod. huang 6	huang 7	mod. huang 7	impl. qr5	qr lapack	svd lapack	gqr lapack	total
huang6		11	4	7	17	16	9	13	77
mod.huang6	10		6/2	9	15/1	13	10	11/1	74/4
huang7	17	13/2		9	16	16	12	12	95/2
mod.huang7	14	12	12		17	14/1	13	13	95/1
impl.qr5	4	5/1	5	4		8	7	7	40/1
qr lapack	5	8	5	6/1	13		9	9	55/1
svd lapack	12	11	9	8	14	12		13	79
gqr lapack	8	9/1	9	8	14	12	8		68/1

From the results in the Appendix and the above tables we can state the following conclusions:

(1) When solving well-conditioned overdetermined systems, the explicit QR algorithms based on the Householder orthogonalization are usually faster than ABS methods tested (especially if $n >> m/2$). Therefore, we cannot recommend the later for solving standard problems.

(2) Interesting results were obtained for extremely ill-conditioned problems. The modified Huang and the implicit QR algorithms failed to solve systems with the matrix IDF2. Such systems was not solved by simple explicit QR methods as well. On the other hand, the modified Huang and the implicit QR algorithms found solutions of systems with the matrix IDF3 extremely fast and, moreover, they were able to determine the numerical rank correctly. Performance of these algorithms in that particular case is remarkable, they are at least 20 times faster then the best LAPACK routines.

(3) The LAPACK routine DGELSS based on the SVD decomposition is extremely slow (especially if $n >> m/2$), not suitable for solving our problems (it can be substituted by the much faster routine DGELSX).

(4) In term of solution error mod-huang7 and gqr are the best; in term of residual error huang7 and mod.huang7 are the best.

References

[1] J.Abaffy, C.G.Broyden, E.Spedicato: A class of direct methods for linear systems. Numerische Mathematik 45 (1984) pp. 361-376.

[2] J.Abaffy, E.Spedicato: ABS Projection Algorithms, Mathematical Techniques for solving Linear and Nonlinear Equations. Ellis Horwood, Chichester 1989.

[3] E.Bodon: Numerical results on the ABS algorithms for linear systems of equations. Rept. No. DMSIA 93/13, University of Bergamo, 1993.

[4] E.Bodon, L. Lukšan, E. Spedicato: Computational experience with ABS algorithms for determined and underdetermined linear systems, rept. No. DMSIA 00/21, University of Bergamo, 2000.

[5] H.Y.Huang: A direct method for the general solution of a system of linear equations. JOTA 16 (1975) pp. 429-445.

[6] E.Spedicato: ABS algorithms for linear least squares: Theoretical results and computational performance. Rept. No. DMSIA 94/2, University of Bergamo, 1994.

[7] E.Spedicato, E.Bodon: Numerical behaviour of the implicit QR algorithm in the ABS class for linear least squares. Ricerca Operativa 22 (1992) pp.45-55.

[8] E.Spedicato, E.Bodon: Solving linear least squares by orthogonal factorization and pseudoinverse computation via the modified Huang algorithm in the ABS class. Computing 42 (1989) pp. 195-205.

[9] E.Spedicato, E.Bodon: Solution of linear least squares via the ABS algorithms. Mathematical Programming 58 (1993) pp. 111-136.

[10] E.Spedicato, H.Esmaeili, Z.Xia: A review of ABS algorithms for linear real and Diophantine equations and optimization. In: Proc. of the VI CMA Congresso de Matematica Aplicada (R.Montenegro, G.Montero, G.Winter, eds.), Las Palmas, Gran Canaria, September 1999.

[11] E.Spedicato, M.T.Vespucci: Variations on the Gramm-Schmidt and the Huang algorithms for linear systems: a numerical study. Applications of Mathematics 2 (1223), 81-100.

[12] E.Bodon: ABS codes for linear determined, underdetermined and overdetermined systems, Rept. No. DMSIA 00/24, University of Bergamo, 2000

4 Appendix: Test results on overdetermined linear systems

matrix	dimension		method	solution error	residual error	rank	time
IR500	1050	950	huang6	0.17D-01	0.23D-14	950	32.00
IR500	1050	950	mod.huang6	0.78D-10	0.20D-15	950	63.00
IR500	1050	950	huang7	0.17D-01	0.16D-14	950	30.00
IR500	1050	950	mod.huang7	0.79D-10	0.85D-15	950	60.00
IR500	1050	950	impl.qr5	0.51D-09	0.12D-13	950	57.00
IR500	1050	950	qr lapack	0.84D-09	0.83D-14	950	16.00
IR500	1050	950	svd lapack	0.31D-08	0.80D-14	950	119.00
IR500	1050	950	gqr lapack	0.28D-08	0.28D-14	950	26.00
condition number:			0.42D+09				
IR500	1400	700	huang6	0.13D-02	0.51D-14	700	23.00
IR500	1400	700	mod.huang6	0.41D-11	0.12D-13	700	49.00
IR500	1400	700	huang7	0.13D-02	0.82D-14	700	24.00
IR500	1400	700	mod.huang7	0.39D-11	0.15D-14	700	47.00
IR500	1400	700	impl.qr5	0.33D-10	0.31D-13	700	40.00
IR500	1400	700	qr lapack	0.54D-10	0.56D-14	700	15.00
IR500	1400	700	svd lapack	0.54D-10	0.18D-13	700	67.00
IR500	1400	700	gqr lapack	0.23D-09	0.77D-14	700	23.00
condition number:			0.65D+08				

Test results for overdetermined linear systems - continued

matrix	dimension		method	solution error	residual error	rank	time
m	n						
IR500	2000	400	huang6	0.35D-03	0.95D-15	400	12.00
IR500	2000	400	mod.huang6	0.96D-12	0.78D-15	400	21.00
IR500	2000	400	huang7	0.35D-03	0.41D-15	400	11.00
IR500	2000	400	mod.huang7	0.87D-12	0.33D-15	400	21.00
IR500	2000	400	impl.qr5	0.55D-11	0.11D-13	400	18.00
IR500	2000	400	qr lapack	0.18D-10	0.46D-13	400	7.00
IR500	2000	400	svd lapack	0.18D-10	0.54D-13	400	20.00
IR500	2000	400	gqr lapack	0.65D-10	0.10D-12	400	12.00
condition number:			0.24D+08				
IR500C	1050	950	huang6	0.23D-01	0.15D-14	950	33.00
IR500C	1050	950	mod.huang6	0.11D-01	0.19D-14	950	63.00
IR500C	1050	950	huang7	0.23D-01	0.36D-16	950	30.00
IR500C	1050	950	mod.huang7	0.11D-01	0.11D-14	950	60.00
IR500C	1050	950	impl.qr5	0.12D-01	0.40D-12	950	57.00
IR500C	1050	950	qr lapack	0.45D-02	0.36D-14	950	17.00
IR500C	1050	950	svd lapack	0.69D+00	0.41D-14	949	114.00
IR500C	1050	950	gqr lapack	0.69D+00	0.19D-14	949	26.00
condition number:			0.25D+14				
IR500C	1400	700	huang6	0.27D+00	0.11D-14	700	24.00
IR500C	1400	700	mod.huang6	0.21D-05	0.34D-15	700	49.00
IR500C	1400	700	huang7	0.27D+00	0.62D-15	700	24.00
IR500C	1400	700	mod.huang7	0.21D-05	0.23D-15	700	47.00
IR500C	1400	700	impl.qr5	0.12D+01	0.65D-14	700	29.00
IR500C	1400	700	qr lapack	0.35D-06	0.11D-15	700	15.00
IR500C	1400	700	svd lapack	0.35D-06	0.80D-15	700	66.00
IR500C	1400	700	gqr lapack	0.11D-05	0.32D-14	700	22.00
condition number:			0.51D+12				
IR500C	2000	400	huang6	0.11D-01	0.31D-14	400	11.00
IR500C	2000	400	mod.huang6	0.33D-03	0.18D-14	400	21.00
IR500C	2000	400	huang7	0.11D-01	0.50D-15	400	11.00
IR500C	2000	400	mod.huang7	0.33D-03	0.37D-15	400	21.00
IR500C	2000	400	impl.qr5	0.80D-03	0.23D-13	400	18.00
IR500C	2000	400	qr lapack	0.10D-02	0.37D-15	400	7.00
IR500C	2000	400	svd lapack	0.70D+00	0.55D-15	399	19.00
IR500C	2000	400	gqr lapack	0.70D+00	0.19D-13	399	11.00
condition number:			0.52D+13				

Test results for overdetermined linear systems - continued

matrix	dimension		method	solution error	residual error	rank	time
RR100	1050	950	huang6	0.59D-10	0.21D-14	950	32.00
RR100	1050	950	mod.huang6	0.96D-14	0.25D-14	950	63.00
RR100	1050	950	huang7	0.59D-10	0.93D-15	950	30.00
RR100	1050	950	mod.huang7	0.85D-14	0.58D-15	950	61.00
RR100	1050	950	impl.qr5	0.82D-14	0.31D-14	950	57.00
RR100	1050	950	qr lapack	0.79D-14	0.19D-15	950	16.00
RR100	1050	950	svd lapack	0.20D-13	0.30D-14	950	158.00
RR100	1050	950	gqr lapack	0.80D-14	0.26D-14	950	26.00
condition number:			0.35D+04				
RR100	1400	700	huang6	0.25D-11	0.47D-12	700	24.00
RR100	1400	700	mod.huang6	0.44D-14	0.99D-12	700	48.00
RR100	1400	700	huang7	0.25D-11	0.99D-12	700	24.00
RR100	1400	700	mod.huang7	0.24D-14	0.85D-13	700	47.00
RR100	1400	700	impl.qr5	0.35D-14	0.54D-12	700	40.00
RR100	1400	700	qr lapack	0.28D-14	0.49D-12	700	15.00
RR100	1400	700	svd lapack	0.86D-14	0.91D-12	700	84.00
RR100	1400	700	gqr lapack	0.36D-14	0.16D-11	700	22.00
condition number:			0.49D+03				
RR100	2000	400	huang6	0.18D-11	0.40D-14	400	11.00
RR100	2000	400	mod.huang6	0.55D-14	0.49D-15	400	22.00
RR100	2000	400	huang7	0.18D-11	0.41D-14	400	11.00
RR100	2000	400	mod.huang7	0.21D-14	0.12D-14	400	21.00
RR100	2000	400	impl.qr5	0.60D-14	0.33D-15	400	18.00
RR100	2000	400	qr lapack	0.30D-14	0.59D-14	400	8.00
RR100	2000	400	svd lapack	0.84D-14	0.74D-14	400	22.00
RR100	2000	400	gqr lapack	0.27D-14	0.15D-13	400	11.00
conition number:			0.26D+03				
IDF1	1050	950	huang6	0.17D-03	0.25D-14	950	32.00
IDF1	1050	950	mod.huang6	0.44D-10	0.23D-16	950	63.00
IDF1	1050	950	huang7	0.17D-03	0.98D-15	950	30.00
IDF1	1050	950	mod.huang7	0.24D-10	0.23D-17	950	60.00
IDF1	1050	950	impl.qr5	0.32D-07	0.42D-12	950	58.00
IDF1	1050	950	qr lapack	0.23D-09	0.14D-14	950	17.00
IDF1	1050	950	svd lapack	0.22D-09	0.16D-14	950	128.00
IDF1	1050	950	gqr lapack	0.18D-09	0.52D-14	950	29.00
condition number:			0.15D+08				

Test results for overdetermined linear systems - continued

matrix	dimension		method	solution error	residual error	rank	time
IDF1	1400	700	huang6	0.53D-03	0.21D-14	700	23.00
IDF1	1400	700	mod.huang6	0.61D-10	0.11D-14	700	47.00
IDF1	1400	700	huang7	0.53D-03	0.11D-14	700	24.00
IDF1	1400	700	mod.huang7	0.23D-10	0.45D-15	700	47.00
IDF1	1400	700	impl.qr5	0.28D-07	0.30D-12	700	43.00
IDF1	1400	700	qr lapack	0.24D-09	0.23D-14	700	15.00
IDF1	1400	700	svd lapack	0.23D-09	0.89D-15	700	63.00
IDF1	1400	700	gqr lapack	0.23D-09	0.33D-14	700	23.00
condition number:			0.18D+08				
IDF1	2000	400	huang6	0.12D-02	0.17D-14	400	11.00
IDF1	2000	400	mod.huang6	0.14D-09	0.90D-15	400	22.00
IDF1	2000	400	huang7	0.12D-02	0.21D-15	400	11.00
IDF1	2000	400	mod.huang7	0.31D-10	0.98D-15	400	21.00
IDF1	2000	400	impl.qr5	0.20D-07	0.18D-12	400	17.00
IDF1	2000	400	qr lapack	0.36D-09	0.97D-15	400	8.00
IDF1	2000	400	svd lapack	0.36D-09	0.87D-15	400	17.00
IDF1	2000	400	gqr lapack	0.52D-09	0.82D-16	400	12.00
condition number:			0.33D+08				
IDF2	1050	950	huang6	0.65D+03	0.18D-12	950	29.00
IDF2	1050	950	mod.huang6	0.83D+10	0.86D-05	4	1.00
IDF2	1050	950	huang7	0.65D+03	0.76D-13	950	30.00
IDF2	1050	950	mod.huang7	0.83D+10	0.17D-05	4	0.00
IDF2	1050	700	impl.qr5	--- break-down ---			
IDF2	1050	950	qr lapack	0.11D+14	0.11D-05	950	16.00
IDF2	1050	950	svd lapack	0.10D+01	0.36D-15	3	138.00
IDF2	1050	950	gqr lapack	0.10D+01	0.31D-15	3	25.00
condition number:			0.11D+21				
IDF2	1400	700	huang6	0.18D+04	0.97D-12	700	20.00
IDF2	1400	700	mod.huan	0.23D+11	0.50D-04	4	1.00
IDF2	1400	700	huang7	0.18D+04	0.38D-12	700	20.00
IDF2	1400	700	mod.huang7	0.23D+11	0.35D-04	4	0.00
IDF2	1050	700	impl.qr5	--- break-down ---			
IDF2	1400	700	qr lapack	0.32D+13	0.41D-06	700	14.00
IDF2	1400	700	svd lapack	0.10D+01	0.29D-15	3	74.00
IDF2	1400	700	gqr lapack	0.10D+01	0.68D-15	3	21.00
condition number:			0.45D+20				

Test results for overdetermined linear systems - continued

matrix m	dimension n		method	solution error	residual error	rank	time
IDF2	2000	400	huang6	0.10D+04	0.51D-12	400	9.00
IDF2	2000	400	mod.huang6	0.76D+10	0.33D-05	4	0.00
IDF2	2000	400	huang7	0.10D+04	0.50D-12	400	9.00
IDF2	2000	400	mod.huang7	0.76D+10	0.45D-05	4	0.00
IDF2	1050	700	impl.qr5	--- break-down ---			
IDF2	2000	400	qr lapack	0.91D+12	0.22D-07	400	7.00
IDF2	2000	400	svd lapack	0.10D+01	0.68D-15	3	18.00
IDF2	2000	400	gqr lapack	0.10D+01	0.29D-14	3	11.00
condition number:			0.17D+20				
IDF3	1050	950	huang6	0.32D+04	0.80D-13	950	30.00
IDF3	1050	950	mod.huang6	0.14D+04	0.14D-11	2	1.00
IDF3	1050	950	huang7	0.32D+04	0.52D-13	950	31.00
IDF3	1050	950	mod.huang7	0.14D+04	0.20D-09	2	0.00
IDF3	1050	950	impl.qr	0.14D+04	0.99D-15	2	0.00
IDF3	1050	950	qr lapack	0.37D+13	0.83D-02	950	17.00
IDF3	1050	950	svd lapack	0.10D+01	0.24D-14	2	145.00
IDF3	1050	950	gqr lapack	0.10D+01	0.22D-14	2	27.00
condition number:			0.16D+21				
IDF3	1400	700	huang6	0.72D+03	0.24D-12	700	21.00
IDF3	1400	700	mod.huang6	0.89D+03	0.17D-11	2	0.00
IDF3	1400	700	huang7	0.72D+03	0.51D-13	700	21.00
IDF3	1400	700	mod.huang7	0.89D+03	0.30D-09	2	0.00
IDF3	1400	700	impl.qr5	0.89D+03	0.17D-11	2	0.00
IDF3	1400	700	qr lapack	0.10D+13	0.17D-02	700	15.00
IDF3	1400	700	svd lapack	0.10D+01	0.31D-13	2	76.00
IDF3	1400	700	gqr lapack	0.10D+01	0.29D-13	2	24.00
condition number:			0.27D+20				
IDF3	2000	400	huang6	0.38D+04	0.58D-12	400	10.00
IDF3	2000	400	mod.huang6	0.44D+03	0.94D-16	2	0.00
IDF3	2000	400	huang7	0.38D+04	0.35D-12	400	9.00
IDF3	2000	400	mod.huang7	0.44D+03	0.67D-12	2	0.00
IDF3	2000	400	impl.qr5	0.44D+03	0.62D-16	2	0.00
IDF3	2000	400	qr lapack	0.45D+12	0.24D-02	400	8.00
IDF3	2000	400	svd lapack	0.10D+01	0.65D-15	2	17.00
IDF3	2000	400	gqr lapack	0.10D+01	0.19D-14	2	12.00
condition number:			0.63D+19				

Test results for overdetermined linear systems - continued

matrix	dimension		method	solution error	residual error	rank	time
IR50	1050	950	huang6	0.10D+02	0.34D-15	950	33.00
IR50	1050	950	mod.huang6	0.92D+01	0.35D-13	773	61.00
IR50	1050	950	huang7	0.10D+02	0.66D-14	950	32.00
IR50	1050	950	mod.huang7	0.92D+01	0.48D-13	773	58.00
IR50	1050	950	impl.qr5	0.92D+01	0.68D-13	773	52.00
IR50	1050	950	qr lapack	0.44D+12	0.16D-01	950	17.00
IR50	1050	950	svd lapack	0.41D+00	0.13D-13	773	96.00
IR50	1050	950	gqr lapack	0.41D+00	0.17D-13	773	28.00
condition number:			0.65D+21				
IR50	1400	700	huang6	0.22D+02	0.29D-13	700	24.00
IR50	1400	700	mod.huang6	0.64D+01	0.12D-12	618	48.00
IR50	1400	700	huang7	0.22D+02	0.26D-13	700	24.00
IR50	1400	700	mod.huang7	0.64D+01	0.18D-13	618	48.00
IR50	1400	700	impl.qr5	0.64D+01	0.57D-13	618	37.00
IR50	1400	700	qr lapack	0.34D+12	0.87D-01	700	15.00
IR50	1400	700	svd lapack	0.36D+00	0.62D-13	618	50.00
IR50	1400	700	gqr lapack	0.36D+00	0.11D-12	618	22.00
condition number:			0.43D+21				
IR50	2000	400	huang6	0.41D+04	0.30D-11	400	10.00
IR50	2000	400	mod.huang6	0.45D+00	0.12D-14	374	20.00
IR50	2000	400	huang7	0.41D+04	0.71D-12	400	11.00
IR50	2000	400	mod.huang7	0.45D+00	0.24D-14	374	21.00
IR50	2000	400	impl.qr5	0.45D+00	0.43D-14	374	17.00
IR50	2000	400	qr lapack	0.80D+12	0.19D+00	400	7.00
IR50	2000	400	svd lapack	0.33D+00	0.14D-13	374	18.00
IR50	2000	400	gqr lapack	0.33D+00	0.11D-12	374	11.00
condition number:			0.11D+21				